


Product Overview

The QPB7420 is a GaAs pHEMT single ended RF amplifier IC featuring 20dB of flat gain and low noise. This IC is designed to support Fiber to The Home (FTTH) applications from 47 to 1218MHz using a single 5V supply, or it can be used from 3V to 8V depending on linearity requirements. QPB7420 offers low noise and distortion plus high gain in a SOT-89 package for convenient layout and design in set top and infrastructure projects for 75 Ω CATV and satellite applications.



3-pin SOT-89 Package

Functional Block Diagram



Top View

Key Features

- 47 MHz to 1218 MHz Operation
- 3 V, 5 V, and 8 V Operation
- Gain; 20 dB Typical
- Noise Figure; 1.1 dB Typical at 850 MHz
- Adjustable Bias Using External Resistors
- Convenient SOT-89 Package
- RoHS Compliant

Applications

- FTTH GPON and GEPON
- DOCSIS 3.1
- Head End CMTS Equipment
- Optical Node
- Satellite Low Noise Amplifier
- Cable Modem and Set Top Box

Ordering Information

Part Number	Description
QPB7420SQ	Sample bag with 25 pieces
QPB7420SR	7" Reel with 100 pieces
QPB7420TR13	13" Reel with 2500 pieces
QPB7420PCK-1	47 – 1218 MHz PCBA with 5 pc sample bag

Absolute Maximum Ratings

Parameter	Rating
Supply Voltage (V_{DD})	+10 V
Supply Current (I_{DD})	140 mA
Maximum Input Level	65 dBmV
Operating Temperature Range	-40 to +85 °C
Storage Temperature Range	-65 to +150 °C
Maximum Junction Temperature	+150 °C

Exceeding any one or a combination of the Absolute Maximum Rating conditions may cause permanent damage to the device. Extended application of Absolute Maximum Rating conditions to the device may reduce device reliability.

Electrical Specifications – 3 V

Parameter	Condition ⁽¹⁾	Min	Typ	Max	Unit
Supply Voltage (V_{DD})			3		V
Supply Current (I_{DD})			35		mA
Frequency Range		47		1218	MHz
Gain			20		dB
Gain Slope			1.0		dB
Reverse Isolation			22		dB
Input Return Loss			21		dB
Output Return Loss			21		dB
Noise Figure			1.3		dB
CSO	20 dBmV / ch output, 80 NTSC + 108 QAM, flat		54		dBc
CTB	20 dBmV / ch output, 80 NTSC + 108 QAM, flat		75		dBc
CCN	20 dBmV / ch output, 80 NTSC + 108 QAM, flat		52		dB
OIP2L	7 dBm / tone output		38		dBm
OIP2H	7 dBm / tone output		37		dBm
OIP3	7 dBm / tone output		28		dBm
OP1dB			15.3		dBm
Thermal Resistance	Θ_{JC}		35		°C/W

Notes:

1. Typical performance at these conditions: Temp = +25 °C, V_{DD} = +5 V, 75 Ω system, Full band unless otherwise noted

Electrical Specifications – 5 V

Parameter	Condition ⁽¹⁾	Min	Typ	Max	Unit
Supply Voltage (V_{DD})			5		V
Supply Current (I_{DD})			55		mA
Frequency Range		47		1218	MHz
Gain			20.4		dB
Gain Slope			1.1		dB
Reverse Isolation			23		dB
Input Return Loss			23		dB
Output Return Loss			20		dB
Noise Figure			1.2		dB
CSO	20 dBmV / ch output, 80 NTSC + 108 QAM, flat		60		dBc
CTB	20 dBmV / ch output, 80 NTSC + 108 QAM, flat		77		dBc
CCN	20 dBmV / ch output, 80 NTSC + 108 QAM, flat		55		dB
OIP2L	7 dBm / tone output		44		dBm
OIP2H	7 dBm / tone output		41		dBm
OIP3	7 dBm / tone output		35.5		dBm
OP1dB			20		dBm
Thermal Resistance	Θ_{JC}		35		$^{\circ}\text{C/W}$

Notes:

1. Typical performance at these conditions: Temp = +25 $^{\circ}\text{C}$, V_{DD} = +5V, 75 Ω system, Full band unless otherwise noted

**Electrical Specifications – 8 V**

Parameter	Condition ⁽¹⁾	Min	Typ	Max	Unit
Supply Voltage (V_{DD})			8		V
Supply Current (I_{DD})			90		mA
Frequency Range		47		1218	MHz
Gain			20.6		dB
Gain Slope			1.1		dB
Reverse Isolation			23		dB
Input Return Loss			19		dB
Output Return Loss			17		dB
Noise Figure			1.3		dB
CSO	28 dBmV / ch output, 80 NTSC + 108 QAM, flat		60		dBc
CTB	28 dBmV / ch output, 80 NTSC + 108 QAM, flat		76		dBc
CCN	28 dBmV / ch output, 80 NTSC + 108 QAM, flat		59		dB
OIP2L	7 dBm / tone output		52		dBm
OIP2H	7 dBm / tone output		47		dBm
OIP3	7 dBm / tone output		40		dBm
OP1dB			24.2		dBm
Thermal Resistance	Θ_{JC}		35		$^{\circ}\text{C/W}$

Notes:

1. Typical performance at these conditions: Temp = +25 $^{\circ}\text{C}$, V_{DD} = +5 V, 75 Ω system, Full band unless otherwise noted


**Evaluation Board Bill of Materials**

Designator	Description	Manufacturer	Part Number
PCB	QPB7420-4000	DDI	QPB7420-4000(A)
U1	20dB FTTH Amplifier	Qorvo	QPB7420SB
B1	RES, 0 Ω , 5%, 1/10W, 0402	Kamaya, Inc	RMC1/16SJPTH
B2	FER, BEAD, 1.8K, 200mA, 0402	TDK	MMZ1005A182ET000
C1, C2, C5	CAP, 0.01 μ F, 10%, 50V, X7R, 0402	Murata Electronics	GRM155R71H103KA88D
C3	CAP, 0.6pF, +/-0.1pF, 50V, HI-Q, 0402	Murata Electronics	GJM1555C1HR60BB01D
C4	CAP, 0.3pF, +/-0.05pF, 50V, C0G, 0402	Murata Electronics	GRM1555C1HR30WA01D
C6	CAP, 330pF, 5%, 50V, C0G, 0402	Murata Electronics	GRM1555C1H331JA01D
J1, J2	CONN, F FEM EDGE MOUNT, 75 OHMS, 0.068"	Millimeter Wave Technologies, LLC	MW-846-C-DD-75
J3, J4	TERM. SOLDER TURRET, 0.062 PCB	Mill-Max Manufacturing	2533-0-00-44-00-00-07-0
L1, L2	IND, 6.8nH, 5%, M/L, 0402	Murata Electronics	LQG15HN6N8J02D
L3	IND, 47nH, 5%, M/L, 0402	Murata Electronics	LQG15HN47NJ02D
R1	RES, 910 Ω , 5%, 1/16W, 0402	Panasonic Industrial	ERJ-2GEJ911X
R2	RES, 200 Ω , 5%, 1/16W, 0402	Kamaya, Inc	RMC1/16S-201JTH
R3, R4, R5, C7	Not Populated		

Evaluation Board Assembly Drawing









Typical Application Schematic, 47 MHz – 1218 MHz



Notes:







1. C3/L1 tunes the input return loss
2. L2/C4 tunes the output return loss with some contribution from C6.
3. R1/L3 sets the level of feedback while B2 provides the bias path with RF isolation from the RF output path.
4. R2 helps control high end tilt/peaking.
5. 1 MΩ Resistor can be added from the input to VDD to increase linearity, trading off degraded noise figure and return loss.

Performance Data – 5 V



Notes:
(1) OIP3: 7 dBm/tone output





Performance Data – 5 V



Notes:

- (1) OIP2: 7 dBm / tone output
- (2) CSO/CTB, CCN: 20 dBmV / ch output, 80 NTSC + 108 QAM, flat
- (3) MER: 190 QAM256 Channels, 57-1215MHz, ITU-T J.83, Annex B







Performance Data – 5 V



Notes:







(1) 1 M Ω Pullup installed in R3, 0 Ω installed in R5. Refer to Evaluation Board Schematic on Pg 5.

Performance Data vs Supply Voltage









Notes:
(1) OIP3: 7 dBm/ tone output

Performance Data – Supply Voltage



- Notes:
- (1) OIP2: 7 dBm / tone output
 - (2) CSO/CTB, CCN: 20 dBmV / ch output, 80 NTSC + 108 QAM, flat


Performance Data – Supply Voltage



Notes:

- (1) CSO/CTB, CCN: 28 dBmV/ch output, 80 NTSC + 108 QAM, flat
- (2) MER: 190 QAM256 Channels, 57-1215MHz, ITU-T J.83, Annex B

Pin Configuration and Description




Top View

Pin Number	Label	Description
1	RF IN	RF Input, DC blocking capacitor required
2	GND	Internally Not Connected
3	RF OUT / VDD	RF Output – VDD bias choke required
Backside Paddle	GND	Ground. Use recommended via pattern to minimize inductance and thermal resistance. See PCB Mounting Pattern for suggested footprint.

Package Outline

NOTES:


1. SHADED LEAD IS PIN 1.




Notes:

1. Dimensions in millimeters

Package Marking



Recommended Mounting Pattern



Notes:

1. Ground/thermal vias are critical for the proper performance of this device. Vias should use a .35 mm (#80/.0135") diameter drill and have a final, plated thru diameter of 0.25 mm (0.010").
2. Add as much copper as possible to inner and outer layers near the part to ensure optimal thermal performance.
3. RF trace width depends upon the PC board material and construction.
4. All dimensions are in millimeters (inches). Angles are in degrees.

Handling Precautions

Parameter	Rating	Standard
ESD – Human Body Model (HBM)	1B (500V)	ESDA / JEDEC JS-001-2012
ESD – Charged Device Model (CDM)	C1 (1000V)	JEDEC JESD22-C101F
MSL – Moisture Sensitivity Level	MSL1	IPC/JEDEC J-STD-020



Caution!
ESD-Sensitive Device

Solderability

Compatible with both lead-free (260 °C max. reflow temp.) and tin/lead (245 °C max. reflow temp.) soldering processes.

Solder profiles available upon request.


Contact plating: Matte Sn

RoHS Compliance

This part is compliant with 2011/65/EU RoHS directive (Restrictions on the Use of Certain Hazardous Substances in Electrical and Electronic Equipment) as amended by Directive.

This product also has the following attributes:

- Lead Free
- Halogen Free (Chlorine, Bromine)
- Antimony Free
- TBBP-A (C₁₅H₁₂Br₄O₂) Free
- PFOS Free
- SVHC Free



Contact Information

For the latest specifications, additional product information, worldwide sales and distribution locations:

Tel: **1-844-890-8163**

Web: www.qorvo.com

Email: customer.support@qorvo.com

Important Notice

The information contained herein is believed to be reliable; however, Qorvo makes no warranties regarding the information contained herein and assumes no responsibility or liability whatsoever for the use of the information contained herein. All information contained herein is subject to change without notice. Customers should obtain and verify the latest relevant information before placing orders for Qorvo products. The information contained herein or any use of such information does not grant, explicitly or implicitly, to any party any patent rights, licenses, or any other intellectual property rights, whether with regard to such information itself or anything described by such information. **THIS INFORMATION DOES NOT CONSTITUTE A WARRANTY WITH RESPECT TO THE PRODUCTS DESCRIBED HEREIN, AND QORVO HEREBY DISCLAIMS ANY AND ALL WARRANTIES WITH RESPECT TO SUCH PRODUCTS WHETHER EXPRESS OR IMPLIED BY LAW, COURSE OF DEALING, COURSE OF PERFORMANCE, USAGE OF TRADE OR OTHERWISE, INCLUDING THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE.**

Without limiting the generality of the foregoing, Qorvo products are not warranted or authorized for use as critical components in medical, life-saving, or life-sustaining applications, or other applications where a failure would reasonably be expected to cause severe personal injury or death.

Copyright 2018 © Qorvo, Inc. | Qorvo is a registered trademark of Qorvo, Inc.

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Qorvo:](#)

[QPB7420SR](#) [QPB7420TR13](#) [QPB7420PCK](#)