

# Series 805 Mighty Mouse Triple-Start Protective Cover

## 667-261 and 667-262 Ordering Information



**Plug Cover**

**Protect Connectors From Damage**  
Machined aluminum or stainless steel protective covers have fluorosilicone gasket for a watertight fit.



**Receptacle Cover**

**Stainless Steel Fittings and Rings**  
Choose small diameter eye fittings for panel attachment. Larger rings fit under the jam nut or over cable jackets. Split rings can be installed on fully assembled cables.

**Polyurethane-Coated SST Wire Rope** provide resistance and good flexibility. Or, choose a Fluoropolymer jacket for high temperature exposure.

**Braided Nylon Rope** provides excellent flexibility and good abrasion resistance, and can be ordered with slip knot fittings for easy installation on any size cable.

How To Order	
<b>Sample Part Number</b>	<b>667-262</b> -M -G 9 04 -6
<b>Series (See Table I)</b>	<b>667-261</b> = Plug Cover <b>667-262</b> = Receptacle Cover
<b>Shell Material / Finish</b>	<b>C</b> = Aluminum / Black Anodize (Non-Conductive) RoHS Compliant <b>M</b> = Aluminum / Electroless Nickel RoHS Compliant <b>NF</b> = Aluminum / Cadmium with Olive Drab Chromate <b>ZNU</b> = Aluminum / Zinc-Nickel with Black Chromate <b>MT</b> = Aluminum / Nickel-PTFE RoHS Compliant <b>Z1</b> = Stainless Steel / Passivated RoHS Compliant
<b>Attachment Type</b>	<b>D</b> = Bead Chain, CRES, Passivate <b>F</b> = Wire Rope, Nylon Jacket <b>G</b> = Nylon Rope <b>H</b> = SST Wire Rope, Fluoropolymer Jacket <b>N</b> = No Attachment <b>R</b> = Wire Rope, PVC Jacket <b>S</b> = SST Sash Chain <b>SK</b> = Nylon Rope With Slip Knot <b>T</b> = SST Wire Rope, No Jacket <b>U</b> = SST Wire Rope, Polyurethane Jacket  "SST" = Stainless Steel
<b>Shell Size</b>	<b>8, 9, 10, 11, 12, 13, 15, 18, 19, 21, 23</b>
<b>Attachment Code (See Table II)</b>	Small Ring = <b>01</b> thru <b>06</b> Large Ring = <b>14</b> thru <b>33</b> Split Ring = <b>50</b> thru <b>68</b>
<b>Attachment Length (inches)</b>	Omit for attachment Type N (No Attachment) Example "-6" equals six inch length

Table I: Cover Style	
<b>667-261</b> Plug Cover	<b>667-262</b> Receptacle Cover

Table II: Attachment Code	
Omit for attachment types <b>N</b> (No Attachment) and <b>SK</b> (Slip Knot)	
 Small Ring	<b>01</b> - .126 (3.20) I.D. <b>02</b> - .145 (3.68) I.D. <b>04</b> - .188 (4.78) I.D. <b>06</b> - .197 (5.00) I.D.
 Large Ring	<b>14</b> - .385 (9.78) I.D. <b>15</b> - .445 (11.30) I.D. <b>16</b> - .570 (14.48) I.D. <b>17</b> - .635 (16.13) I.D. <b>18</b> - .695 (17.65) I.D. <b>19</b> - .885 (22.48) I.D. <b>20</b> - 1.070 (27.17) I.D. <b>22</b> - 1.210 (30.73) I.D. <b>23</b> - 1.275 (32.39) I.D. <b>25</b> - 1.530 (38.86) I.D. <b>26</b> - .950 (24.13) I.D. <b>27</b> - .766 (19.46) I.D. <b>28</b> - 1.015 (25.78) I.D. <b>29</b> - .315 (8.0) I.D. <b>30</b> - 1.380 (35.05) I.D. <b>31</b> - .820 (20.83) I.D. <b>32</b> - .265 (6.7) I.D. <b>33</b> - .510 (12.95) I.D.
 Split Ring	<b>50</b> - .420 (10.67) I.D. <b>52</b> - .480 (12.19) I.D. <b>54</b> - .635 (16.13) I.D. <b>56</b> - .745 (18.92) I.D. <b>58</b> - .885 (22.48) I.D. <b>60</b> - 1.010 (25.65) I.D. <b>64</b> - 1.125 (28.58) I.D. <b>68</b> - 1.345 (34.16) I.D.

Dimensions in Inches (millimeters) are subject to change without notice.

# Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

## Glenair:

[667-261-NF-G914-6](#) [667-261-NF-G1100-6](#) [667-261-M-U1217-4](#) [667-261-M-H1506-4](#) [667-261-M-N11](#) [667-261-NF-G1116-6](#) [667-261-NF-S1102-4](#) [667-261-NF-G1802-6](#) [667-261-NF-G900-6](#) [667-261-NF-G1808-4](#) [667-261-NF-G1810-6](#) [667-261-NF-G1510-6](#) [667-261-M-N8](#) [667-261-NF-G1217-6](#) [667-261-NF-SK11-6](#) [667-261-NF-U918-2](#) [667-261-M-N12](#) [667-261-NF-N8](#) [667-261-NF-U1154-6](#) [667-261-ZW-H1506-4](#) [667-261-M-N19](#) [667-261-NF-G952-4](#) [667-261-M-N18](#) [667-261-MT-SK9-3](#) [667-261-NF-H1116-4](#) [667-261-NF-SK18-6](#)